



## NZ2520SHA

## **Automotive safety**

#### **■** Application

For Automotive safety (e.g., Millimeter wave radar or Image processing for self-driving)

#### **■** Features

- High quality and high reliability design for Automotive safety
- Conforms to AEC-Q100/200.
- Supports a wide temperature range from -40 to +125°C.
- Compact and light. Dimensions: 2.5 x 2.0 x 0.9 mm, weight: 0.02 g.
- Taped units enable automatic mounting IR Reflow (lead free) is possible.
- Output Level : CMOS



Absolute maximum rating Supply Voltage (Vcc) -0.3 to +4.0 V Storage Temperature Range -55 to +125 °C







#### ■ Specifications

Item				NZ2520SHA	
Output				CMOS	
Nominal Frequency Range			(MHz)	1.5 to 80	
Overall Frequency Tolerance			(×10 <sup>-6</sup> )	±100	
Operating Temperature Range			(°C)	-40 to +125	
Supply Voltage			(V)	+1.8 to +3.3	
Current Consumption Max.	<b>During Operation</b>	+25 °C	(mA)	2.5 to 9.0	
	During Standby	+25 °C	(µA)	20	
Vol Max. / Voн Min.			(V)	0.1 Vcc / 0.9 Vcc	
Tr Max. / Tf Max. +1.8 V +2.5 to +3.3V		(22)	6 / 6 ( at 0.1 Vcc to 0.9 Vcc )		
		+2.5 to +3.3V	(ns)	5 / 5 ( at 0.1 Vcc to 0.9 Vcc )	
Symmetry Min. to Max.			(%)	45 to 55	
Load (C <sub>L</sub> ) Max.			(pF)	15	
Start-up Time Max. (r			(ms)	4	
Standby function				Available (Three-state)	

#### **■** Dimensions



## ■ Output Waveform < CMOS>



#### ■ Standby Function

#1 Input	#3 Output		
Level H (0.7 $V_{CC} \le V_{IH} \le V_{CC}$ ) or OPEN is selected.	Oscillation output ON		
Level L (V <sub>IL</sub> ≤ 0.3 V <sub>CC</sub> ) is selected.	High impedance		

# Crystal Clock Oscillator NEW



## NZ2520SHA

## **Automotive safety**

### **■** Specification Number

Overall Frequency	Operating Temperature Range (°C)	Supply Voltage (V)				
Tolerance		+1.8±0.18	+2.5±0.25	+3.0±0.3	+3.3±0.33	
±100×10 <sup>-6</sup>	-40 to +125	NSC5072A	NSC5072B	NSC5072C	NSC5072D	

Please specify the model name, frequency, and specification number when you order products.

For further questions regarding specifications, please feel free to contact us.